

Connexx
Accessories




Smart Power

User Guide

Content

Your charger	3
Intended use	4
Explanation of symbols	4
Important notes	5
Notes for batteries	8
How to charge	9
LED legend	9
Preparation	9
Charging and drying	10
Charger status	11
Useful tips for charging	14
Maintenance and care	15
Technical Data	16
Technical data - Country-specific power-supply	17
Disposal information	18

Your charger



1 Charging slots

2 Cavity for receiver units,
tubes and ear pieces

3 Status / power LEDs

4 Contact for
power supply

5 Power supply with
country-specific
adapters

Intended use

This device is intended to charge rechargeable batteries in our specific hearing instruments. Your Hearing Care Professional will advise you on the compatible models.

Read and follow the instructions of this user guide to avoid injuries and to protect the charger and the hearing instruments from damage.

Explanation of symbols



Points out a situation that could lead to serious, moderate, or minor injuries.



Indicates possible property damage.



Advice and tips on how to handle your device better.



Read and follow the instructions in the user guide.

Important notes



NOTICE

Your device is sensitive to extreme heat, high humidity, strong magnetic fields ($> 0.1\text{T}$), X-rays and mechanical stress.

- ▶ Do not expose your device to extreme temperature or high humidity.
- ▶ Do not leave it in direct sunlight.
- ▶ Do not immerse it in water.
- ▶ Do not place your device in a microwave oven.



WARNING

Choking hazard!

Your device contains small parts which can be swallowed.

- ▶ Keep hearing instruments, batteries and accessories out of reach of children and mentally disabled persons.
- ▶ If parts have been swallowed consult a physician or hospital immediately.



WARNING

Risk of electric shock!

- ▶ Do not touch the charging contacts in the charger.
- ▶ If cleaning is required, disconnect the charger from the power supply.



CAUTION

Risk of malfunction through incompatible parts.

- ▶ Use only the power-supply and country-specific adapter that is provided with the charger.



WARNING

Risk of electrical shock!

- ▶ Do not use obviously damaged devices and return them to point of sale.



NOTICE

Please make sure that the power plug is easily accessible to remove it from power supply if necessary.



- This product does not have a power switch. It is turned on when the power cord is plugged in.
- The charger is intended only for indoor use.




DANGER

Incorrect use of the rechargeable battery can cause the rechargeable battery to burst. Discharging chemicals are spontaneously inflammable. Risk of overheating, explosion and fire!

- ▶ Do not ignore the red LED on the charger (refer to the LED status table)!
- ▶ Replace the rechargeable battery when its performance reduces considerably (running time under 8 hours).
- ▶ Do not use the rechargeable batteries when the expiration date on the packaging is exceeded.
- ▶ Do not use damaged or deformed rechargeable batteries.
- ▶ Do not open rechargeable batteries.
- ▶ Do not use rechargeable batteries in explosive environments.
- ▶ In the unlikely event of a burst rechargeable battery, keep all parts away from fire and everything that is readily combustible. Return the parts to your Hearing Care Professional for disposal.

Notes for batteries

- ▶ Use only rechargeable batteries that are provided by your Hearing Care Professional.
- ▶ For information about correct battery size check the user guide of your hearing instruments.
- ▶ Make sure the rechargeable batteries are inserted correctly.
- ▶ Fully charge the rechargeable battery before first use.



NOTICE


- ▶ To avoid environmental pollution, do not throw batteries into household trash.
- ▶ Recycle or dispose of batteries according to national regulations or return them to your Hearing Care Professional.

How to charge

LED legend

The LEDs indicate the status of the charger.

- ① Power LED (green) indicates connection to the power supply.
- ② Status LEDs (multicolor) indicates current charging and drying state of the left/right hearing instrument.



Preparation

- ▶ Connect the charger to a power supply.
The power LED stays on continuously.

Charging and drying

The hearing instruments are first charged and then dried.

- ▶ Press the front button to open the charger and unlock the lid.
- ▶ Place your hearing instruments into the charging slots (refer to the picture).



Please note that the correct function of the charger is only ensured if the ear pieces are placed as shown in the picture.

- ▷ Turn the ear pieces inwards.
- ▷ Do not cross the ear pieces.



- ▶ Close the lid of the charger.

The hearing instruments are switched off automatically and the charging starts.

The status LEDs are blinking.

Charging is complete and the drying cycle has started when the status LEDs stay on continuously.


Drying is complete when the status LEDs are off.

- ▶ Remove the hearing instruments from the charger when you next want to use them.
- ▶ Check if the hearing instruments are turned on.

Charger status

LED and state	Explanation
Power LED is off 	Charger is not connected to the power supply. <ul style="list-style-type: none">▶ Check whether charger is connected to the correct power supply.
Power LED shining green 	No hearing instrument in charger: Charger is connected to power supply. Charger is ready to use. Hearing instruments in charger: Drying process is finished. <ul style="list-style-type: none">▶ Remove hearing instruments from the charger when you want to use them.

LED and state	Explanation
Status LEDs blinking green 	Charging of left/right hearing instrument is ongoing. ► Leave hearing instrument in charger.
Status LEDs shining green 	Charging of left/right hearing instrument is finished. The drying is ongoing. ► Leave hearing instruments in charger.
Status LEDs shining red 	Charging can not be initiated. No hearing instruments in charger: Defect or wrong inlay in the charger. ► Ask your Hearing Care Professional to insert the correct inlay for your hearing instruments. Hearing instruments in charger: Wrong polarity of both instruments. ► Check if batteries are inserted correctly. ► Check if hearing instruments are inserted correctly in charging slots.

LED and state	Explanation
<p data-bbox="130 253 283 323">Status LEDs shining red</p> 	<p data-bbox="355 253 886 323">Wrong polarity of corresponding hearing instrument.</p> <ul style="list-style-type: none"> <li data-bbox="355 334 868 366">▶ Check if battery is inserted correctly. <li data-bbox="355 375 850 445">▶ Check if hearing instruments are inserted correctly in charging slots.
<p data-bbox="130 503 283 573">Status LEDs blinking red</p> 	<p data-bbox="355 503 902 573">Wrong battery in left/right hearing instrument. Charging can not be initiated.</p> <ul style="list-style-type: none"> <li data-bbox="355 585 702 617">▶ Check type of batteries.
<p data-bbox="130 930 283 1038">Status LEDs blinking orange</p> 	<p data-bbox="355 930 897 1154">External temperature is too high. The charging process is interrupted to protect the functionality of the rechargeable batteries. Charging continues when the external temperature drops under 45°C (113°F).</p> <ul style="list-style-type: none"> <li data-bbox="355 1166 881 1198">▶ Place the charger in a cooler location.

Consult your Hearing Care Professional if you encounter problems.

Useful tips for charging

Correct maintenance of your rechargeable batteries will enhance their life time.

- ▶ Avoid charging above 30° C (86°F). It reduces the battery life time.

The rechargeable battery has no memory effect.

- ▶ Charge the battery on a regular basis (e.g. once a day) thus avoiding running it down completely.

A charging cycle takes around 6 hours and the following dring cycle 2 hours (8 hours in total).



If you need to remove the hearing instruments before the charging cycle is complete, the operation time can be shorter than usual.



NOTICE

The rechargeable battery will be damaged or unusable when deep discharged.

- ▶ Only leave the hearing instruments in the charger when the charger is connected to a power supply.
- ▶ Remove the rechargeable batteries from the hearing instruments if you intend not to use them for several days. Charge the rechargeable battery before.

Maintenance and care



NOTICE

The charger will be damaged by dissolver.

- ▶ Do not sterilise or disinfect the charger.
- ▶ Use a dry, soft tissue to clean the charger.
- ▶ Ask your Hearing Care Professional if the charging contacts need cleaning.

Technical Data

Specifications charger	
Operating temperature:	15 ... 35°C / 59 ... 95°F
Operating humidity:	20% ... 75%
Minimum air pressure:	70 kPa
Storage temperature:	-10 ... 40°C / 14 ... 104°F
Storage humidity:	20% ... 75%
Input voltage:	5 V DC
Input current:	< 0.5 A
Protection against electric shock: class II Against ingress of water: IP XO (ordinary)	

Specifications rechargeable batteries p312accu, p13accu; provided by Power One	
Operating temperature (in hearing instrument)	-20 ... 60°C / -4 ... 140°F
Storage temperature (average)	10 ... 26°C / 50 ... 79°F

Technical data - Country-specific power-supply

Kuantech Model KSAA0500080W1UV-1 Kuantech Model KSAS0050500080D5D	
Input voltage:	100-240 V AC
Input current:	0.18 A RMS MAX
Input frequency:	50-60 Hz
Output voltage:	5 V DC
Output current:	0.8 A

Fuhua Model: UE10W-050080SPC	
Input voltage:	100-240 V AC
Input current:	0.15 A RMS MAX
Input frequency:	50-60 Hz
Output voltage:	5 V DC
Output current:	0.8 A

Disposal information

Within the European Union, the marked equipment is covered by "Directive 2002/96/EC of the European Parliament and of the Council of 27 January 2003 on waste electrical and electronic equipment."



Amended by "Directive 2003/108/EC" (WEEE).



- ▶ Recycle devices, batteries and accessories according to national regulations.

With the CE marking Sivantos confirms compliance with the European Directive 2006/95/EC on electrical equipment designed for use within certain voltage limits.



With the CE marking Sivantos confirms compliance with the European Directive 2004/108/EC on electromagnetic compatibility.

 **Legal Manufacturer**

Sivantos GmbH
Henri-Dunant-Strasse 100
91058 Erlangen
Germany
Phone +49 9131 308 0

Connexx is a brand name of Sivantos Group

Document No. A91SAT-02411-99T01-7600 EN
Order/Item No. 109 310 64 | Master Rev01, 11.2014
© Sivantos Group, 12.2014

www.bestsound-technology.com